






ZipControl makes it fast and easy to add remote controls to your UNITY system. Plug and play with no additional programming required, ZipControl acts as a second set of controls that can be installed in a convenient location for the teacher, or for a student to connect an ALD device. Also perfect if you need to install your UNITY in a less accessible location such as a cabinet or behind the panel.

Functions

	 1000-00306 ZipControl Audio	 1000-00307 ZipControl Audio & Alert	 1000-00308 ZipControl Alert
Volume & Mute	✓	✓	
Add Mic Button	✓	✓	
Pair Bluetooth® Button	✓	✓	
Lock Control Panel	✓	✓	
Custom Actions Buttons (2)	✓		
Intercom Button		✓	✓
Alert Button		✓	✓
ALD 3.5mm Output	✓	✓	
Built-in Room Mic		✓	✓
Compatible with UNITY	✓		
Compatible with UNITY Campus		✓	✓

Specifications

	1000-00306 ZipControl Audio	1000-00307 ZipControl Audio & Alert	1000-00308 ZipControl Alert
Weight	170-180 grams	170-180 grams	85-95 grams
Dimensions	117x116x13 mm/ 4.60x4.57x0.51 in	117x116x13 mm/ 4.60x4.57x0.51 in	70x116x11 mm/ 2.76x4.57x0.43 in
Regulatory	FCC, CE, RCM, IC	FCC, CE, RCM, IC	FCC, CE, RCM, IC

Features

- Built-in Microphone for Intercom Communication (when used with UNITY Campus)
- Backlit buttons
- Panel Lock option
- Volume light ring
- Alert light ring
- ALD 3.5mm mono output with volume adjustment
- Screwless snap-on faceplates
- Included green 50ft plenum-rated Cat5e cable connects to color-coded ZipLine port on UNITY
- Fits standard dual gang and single gang boxes and mud rings
- Fits in standard 2" deep gang boxes

ZipControls not Decora® compatible.

Requires UNITY firmware update summer 2025. ZipControls for UNITY Campus require UNITY hardware revision 9 to utilize microphone support for intercom.

Learn more at boxlight.com